

# SPECIFICATION

[Electronic Version 1.2.8]

## A MATCHED FILTER FOR SCALABLE SPREAD SPECTRUM COMMUNICATIONS SYSTEMS

### Background of Invention

[0001] Field of the Invention. This invention relates to spread spectrum communications. More specifically, this invention relates a filter and use of long, scalable, separable PN sequences to achieve variable communication rates together with low complexity in spread spectrum communications.

[0002] Description of Related Art. A variety of spread spectrum communications systems are well known in the art. Often these systems use very long PN codes to achieve processing gain. However, typically, such prior systems have substantial problems with coherence and frequency error and such problems interfere with achieving the objective of robust spread spectrum communications. Typically, these prior systems also require large matched filters to despread signals, where the use of correlators is inappropriate.

[0003] Although the following cited U.S. patent documents are not necessarily "prior art," the reader is referred to the following U.S. patent documents for general

background material. Each of these patents is hereby incorporated by references in its entirety for the material contained therein.

[0004] U.S. Patent Nos.: 4,351,064; 4,953,178; 4,977,578; Re. 33,875; 5,319,672; 5,400,359; 5,471,509; 5,737,368; 5,740,096; 5,790,588; 5,790,590; 5,815,055; 5,881,099; 5,909,461; 5,912,644; 5,926,512; 5,974,082; 5,991,332; 6,031,415; 6,104,746; 6,128,332; 6,154,482; 6,154,487; 6,212,219; 6,233,272; 6,265,807; 6,317,452; 6,331,998; 6,333,925; 6,356,555; 6,434,185; 6,493,334; 6,493,376; 6,549,567; 6,556,621; 6,560,270; 6,560,271; 6,567,017; 6,570,865; 6,580,750; and 6,590,881.

## Summary of Invention

[0005] It is desirable to provide a method and system for the use of long, scalable PN sequences in long distance spread spectrum communications systems. Moreover it is also desirable to provide a low-complexity matched filter architecture that provides robust recovery of multiple devices in a long reach, high ambient noise environments.

[0006] Accordingly, is an object of this invention to provide a method and system for long distance spread spectrum communications systems that makes use of long scalable PN sequences. Moreover, it is an object of this invention to facilitate operation

in high ambient noise environments, by increasing processing gain, to thereby provide the capability to trade off data rate for increased robustness in such high ambient noise environments.

[0007]           Another object of this invention is to provide a method and system for long distance spread spectrum communications system that includes a matched filter with reduced complexity that allows robust recovery of multiple devices in long reach, high ambient noise environments.

[0008]           A further object of this invention is to provide a method and system for long distance spread spectrum communications systems that provides for scalable data rates. A still further object of this invention is to provide a method and system for long distance spread spectrum communications systems that does not require the locking of the receiver to an individual client device.

[0009]           A still further object of this invention is to provide a method and system for scaling the complexity of the receiver, including the matched filter structure, to receive and demodulate transmissions from devices possessing very different frequency tolerances.

[0010]           Another further object of this invention is to provide a method and system for determining the time-of-arrival of a received signal.

[0011] Additional objects, advantages, and other novel features of this invention will be set forth in part in the description that follows and in part will become apparent to those of ordinary skill in the art upon examination of the following, or may be learned with the practice of the invention as described herein. The objects and advantages of this invention may be realized and attained by means of the instrumentalities and combinations particularly pointed out in the appended claims. Still other objects of the present invention will become readily apparent to those skilled in the art from the following description wherein there is shown and described the preferred embodiment of the invention, simply by way of illustration of one of the modes best suited to carry out this invention. As it will be realized, this invention is capable of other different embodiments, and its several details and specific circuits are capable of modification in various aspects without departing from the invention. Accordingly, the objects, drawings and descriptions should be regarded as illustrative in nature and not as restrictive.

## Brief Description of Drawings

[0012] The accompanying drawings incorporated in and forming a part of the specification, illustrate present preferred embodiments of the invention. Some,

although not all, alternative embodiments are described in the following description. In the drawings:

[0013] Figure 1 is a system block diagram showing the major components of one preferred embodiment of the invention.

[0014] Figure 2 is a detailed block diagram of the matched filter architecture of one preferred embodiment of the method of this invention.

[0015] Reference will now be made in detail to the present embodiments of the invention, examples of which are illustrated in the accompanying drawings.

## Detailed Description

[0016] This invention is a filter designed specifically for scalable spread spectrum communications systems and cooperative techniques for the use of long, scalable Pseudo-Noise ("PN") sequences for variable communication rates. Link distance and performance margins in spread spectrum communications can be increased by increasing processing gain. Processing gain is itself directly related to the length of the PN code employed. For example, where the data rate is constrained to one bit per PN sequence, a PN code length of 1000 yields a processing gain of 30 dB, while a PN code length of 10,000 yields a processing gain of 40 dB. In the present invention, long,

scalable PN sequences are used with a low-complexity matched filter architecture to provide variable communication rates, robust recovery of multiple devices in ordinary as well high ambient noise operating environments. In the present invention sites may receive signals, simultaneously or near simultaneously, from a multitude of transmitting devices. Each of these received signals will typically have a corresponding frequency error. Furthermore, the frequency error of the devices may be very different depending on system design objectives, which may be selected to optimize the tradeoffs between variables such as system quality, complexity, cost, and service "class" of the devices. These system requirements tend to preclude locking the receiver to an individual transmitting "client" device in order to achieve frequency coherence across long PN sequences. This invention addresses this problem with a receiver architecture designed so as to facilitate the "simultaneous" receipt of signals, with a wide range of data rates and a wide range of frequency errors, from a variety of devices.

[0017] Referring now to figure 1 shows a system block diagram illustrating the major components of one preferred embodiment of the invention. Data bits 100 are spread 101 by a variable length PNA code 102. Typically, this spread 101 operates to spread the data 100 from 1 to 1023 chips, although in alternative embodiments the spread may be varied without departing from the concept of this invention. The resulting chips 106 are further spread 103 by a fixed length PNB code 104. In the present preferred embodiment of the invention, a chipping rate of 5M CPS is used,

further scaling the data rates from 19.608 kbps to 38 bits/second, providing processing gains of from 24 dB to 51 dB, respectively, depending on the application requirements and the available signal-to-noise ratio in the available link (communication channel). The resulting spread data is transmitted, typically using a radio transmitter 105 for use with an RF link. Table 107 shows the performance of a variety of PNA code lengths. As can be seen, with a constant chip rate, here 5M CPS, as the PNA code length is increased from 1 to 511, the chips per bit increase from 255 to 130305, the processing gain increases from 24 dB to 51 dB and the data rate is reduced from 19608 to 38 bps. Typically, the length of the fixed length PNB code is designed to be short enough to ensure that the worst case frequency error plus the Doppler shift will cause no more than 180 degrees of phase roll, or a correlation loss in the first matched filter of approximately 4 dB.

[0018] Figure 2 shows a detailed block diagram of the matched filter architecture of one preferred embodiment of the method of this invention. The receiver portion of the present data link of this invention includes a radio receiver 201. The output 202 of the receiver 201 provides I & Q channels, which are first processed by a matched filter 203. The matched filter 203 uses the PNB codes as coefficients. Because the frequency can be rolling as much as plus or minus one-hundred eighty degrees across a single PNB code length, a bank of frequency shifters 204, 205, 206, 207, 208, 209, 210, 211 are used prior to sending the filtered data 222 through the PNA matched filters 212, 213,

214, 215, 216, 217, 218, 219, 220. Although, in this figure 2 eight frequency shifters and nine matched filters are shown, the number of each actually employed in a particular embodiment of the invention is dependent on the worst-case frequency roll and the allowable phase error across the concatenated PN codes. The frequency shifters 204, 205, 206, 207, 208, 209, 210, 211 perform a complex frequency shift. The matched filters 212, 213, 214, 215, 216, 217, 218, 219, 220 receive data from the frequency shifters 204, 205, 206, 207, 208, 209, 210, 211 and the matched filter 203 and provide a filtered output signal received by the equalizer/decoder 221. The equalizer/decoder 221 examines the outputs of each matched filter 212, 213, 214, 215, 216, 217, 218, 219, 220 and determines the frequency shift of the received signal and appropriately selects the set of most advantageous signals.

[0019] It is also notable that two smaller matched filters, rather than one large filter is used presently to despread the spread signal. This means, that in the preferred embodiment of this invention, a single long matched filter can be avoided, thereby considerably reducing the amount of signal processing hardware that is required.

[0020] The described embodiment of this invention is to be considered in all respects only as illustrative and not as restrictive. Although specific steps and associated formulas are provided, the invention is not limited thereto. The scope of this invention is, therefore, indicated by the claims rather than by the foregoing description.



All changes, which come within the meaning and range of equivalency of the claims, are to be embraced within their scope.